

Threat Detection

Threat detection's portscan detector is a mechanism designed to help you detect and prevent portscan activity in all types of traffic to protect networks from eventual attacks. Portscan traffic can be detected efficiently in both allowed and denied traffic.

Portscan is a form of network reconnaissance that is often used by attackers as a prelude to an attack. In a portscan, an attacker determines the types of network protocols or services a host supports and sends specially crafted packets to a targeted host. By examining the packets that the host responds with, the attacker can often determine which ports are open on the host and, either directly or by inference, which application protocols are running on these ports.

- Portscan detection and prevention, on page 1
- Requirements and prerequisites for threat detection, on page 3
- Limitations for threat detection configuration, on page 3
- Best practices for portscan prevention, on page 4
- Configure portscan detection and prevention, on page 4
- Monitoring threat detection, on page 6
- History for threat detection, on page 8

Portscan detection and prevention

Portscan detection and prevention is a threat detection system that:

- identifies port scan activity and issues events when they are found,
- optionally prevents port scans by automatically blocking scanners, and
- sends you events and also blocks the attacker for a duration that you set.

Pre-defined sensitivity levels for portscan detection

When configuring detection settings, you select from these pre-defined sensitivity levels. Except for custom, each level has pre-set values for each protocol for the number of ports (TCP, UDP), protocols (IP), or hosts (TCP, UDP, IP, ICMP) that must be scanned within a set time interval (expressed in seconds). Also, all types of scans and sweeps are enabled.

Note When counting ports or protocols, threat detection increments the number if the port or protocol in the current packet differs from the previous packet. For example, if you have an application that opens connections in 10 set ports randomly, the total number of ports scanned could mount so quickly that your port number will be exceeded within the interval. The system does not count only unique ports.

Exceeding the number within the interval can indicate a scanning attack. Portscan events are generated only when the port/protocol/host numbers are exceeded for the moving time interval window.

These sensitivity levels determine portscan detection behavior:

- **Low**—This level uses the shortest time window for portscan detection, coupled with high counts for ports, protocols, and hosts. Thus, you should see portscan events for the most aggressive scanners only. Select this sensitivity level to suppress false positives, but remember that some types of port scans, such as slow or filtered scans, might be missed.
- **Medium**—This level uses moderate values for both the interval and port/protocol/host counts. However, very active hosts such as network address translators and proxies might generate false positives. Add such hosts to the ignore scanner list. This is the default sensitivity level and a good place to start.
- **High**—This level uses a much longer time window for portscan detection, coupled with lower counts for ports, protocols, and hosts. With this level, you are most likely to see events for even the least aggressive port scans or sweeps, so you are more likely to notice all attackers. However, this level would likely result in the most portscan events issued, and potentially the highest number of false positives.
- **Custom**—If you want to configure any setting differently than one of the predefined sensitivity levels, or disable a particular type of scan or sweep, the level automatically switches to custom. If you want to adjust the options, first select the level that most closely matches what you want, then edit the values as appropriate.

Table 1: Sensitivity level settings

Setting	Low	Medium	High
Interval (TCP/UDP/IP/ICMP)	60 seconds	90 seconds	600 seconds (10 minutes)
TCP/UDP portscan - Number of Ports	120 seconds	90 seconds	60 seconds
TCP/UDP portsweep - Number of Hosts	180 seconds	150 seconds	100 seconds
IP protocol scan - Number of Protocols	30 seconds	15 seconds	10 seconds
IP protocol sweep - Number of Hosts	25 seconds	20 seconds	10 seconds
ICMP host sweep - Number of Hosts	50 seconds	30 seconds	20 seconds

Requirements and prerequisites for threat detection

Model support

Firewall Threat Defense running version 7.2+ and Snort 3.

Supported domains

Any

User roles

Admin

Access Admin

Network Admin

Limitations for threat detection configuration

Threat detection requires Snort 3 and has specific version requirements and configuration interactions that vary by management platform.

- Threat detection requires Snort 3. The managed device must be running version 7.2 or higher. For Snort 2, or devices running versions lower than 7.2, you can configure port scan through the NAP policy. Note that the threat detection feature is not the same as the port scan feature in the NAP policy. If there are non-Snort 3 devices running version 7.2 or higher that are assigned to the access control policy, the threat detection settings are not deployed to those unsupported devices.
- If you configure port scan in the NAP policy on a device running 7.1 or lower, that configuration is not translated to the threat detection feature on upgrade to 7.2. You must manually configure threat detection. Although the NAP and threat detection port scan options are similar, they do not match one-to-one.
- If you configure threat detection, any port scan configuration in the NAP policy is ignored and not configured on the devices that support threat detection.
- The NAP port scan feature for Snort 3 is always ignored for devices running version 7.2 or higher. To configure port scanning, you must use the threat defense settings.
- Threat detection works on traffic that passes through the device only. It does not work on traffic directed to the device.
- In a high availability setup, port scanning statistics are not synchronized to the standby unit. However, blocked hosts are synchronized and continue to be blocked until the duration period expires in case of a failover.
- (Devices running Threat Defense versions 7.2 through 7.7). For nodes in a cluster, detection and prevention happen on the individual cluster node. That is, if node B detects and blocks traffic from a host, node A will not be aware of that action because port scan statistics are not synchronized across cluster nodes.
- For inline sets, or for interfaces that are configured to be part of an equal-cost multipath (ECMP) traffic zone, detection and prevention are done at the zone level. Port scan statistics for a host are accumulated

across all interfaces of a zone. Similarly, when a host crosses configured thresholds, it is blocked across all interfaces of the corresponding zone.

- Although the port scan events generated by the threat detection feature are the same as the ones Snort issues for port scan, you do not need to enable port scanning intrusion rules to get the events. Threat detection works regardless of your intrusion policy implementation.

Best practices for portscan prevention

Portscan prevention mode can result in unintended traffic outage. In prevention mode, hosts are blocked from further scanning of networks on all protocols for the configured duration. Review the detection and prevention parameters carefully to ensure legitimate traffic is not blocked.

Before configuring portscan in prevention mode:

- Start using portscan in detection mode.
- Observe the generated portscan events.
- Tune the sensitivity level, monitored networks, ignore scanner list, and ignore target list. If a pre-defined sensitivity level does not work well for your situation, configure custom settings as needed.
- Repeat the process until false positives are eliminated and the event rate represents an accurate picture of port scanning in your network. Ensure that you are comfortable with blocking the remaining identified scanners.

Configure portscan detection and prevention

This task enables threat detection to watch for port scanning activity and optionally automatically block scanners for a period of time.

Portscan is a form of network reconnaissance that is often used by attackers as a prelude to an attack. In a portscan, an attacker determines the types of network protocols or services a host supports and sends specially crafted packets to a targeted host. By examining the packets that the host responds with, the attacker can often determine which ports are open on the host and, either directly or by inference, which application protocols are running on these ports.

You can enable threat detection to watch for port scanning activity and optionally, automatically block scanners for a period of time.

Before you begin

Fully Qualified Domain Name (FQDN), wildcard mask, any, any-ipv4, and any-ipv6 network objects are not supported for portscan configuration. These objects are not shown in the **Monitor**, **Ignore Scanner**, **Ignore Target**, and **Exclude** fields.

Procedure

Step 1 In the access control policy editor, click **Advanced**, then click **Edit** ( ) next to **Threat Detection**.

Step 2 In the **Threat Detection** window, select the **Portscan mode**:

- **Disable**—Turn off threat detection. This is the default mode. You can click **Revert to Defaults** to return to this unconfigured state.
- **Detection**—Perform portscan detection, but alert on problems only. Do not take action against potential attackers. We suggest you use this mode initially until you fine-tune the threat detection settings to avoid excessive false positives.
- **Prevention**—Perform portscan detection and actively block identified scanners, that is, hosts that are performing the port scan.

Step 3 Configure the **Traffic Selection** options.

The traffic selection options determine which networks are monitored, the type of connections monitored, and whether any scanners or target hosts should be exempted from the monitored networks. By default, the system monitors permitted connections on all networks.

- **Detection On Traffic**—Select the types of connection that will be monitored for portscan activity: **Permitted**, **Denied**, or **All** traffic. The default is **Permitted**.
- **Monitor**—Select the network objects that define the networks to monitor for portscan or sweep activity. The default is any network, IPv4 or IPv6. Use this option to limit scanning to untrusted networks.
- **Ignore Scanner**—Select the network objects that define the hosts or networks, from within the range of the monitored networks, that should be ignored. For example, if you have set up your own scanner to test your network, you can exempt the address of your scanner to avoid unnecessary reporting on the address. Do not include addresses that are outside the monitored networks, as these addresses are already ignored.
- **Ignore Target**—Select the network objects that define the hosts or networks that should be ignored as targets, that is, victims of a portscan or sweep.

Step 4 Click the **Configuration** tab and select the scanning sensitivity level.

The predefined sensitivity levels, **Low**, **Medium**, and **High**, set the port scanning options to values that are increasingly aggressive. For example, if you select low, you would expect to see fewer port scanning events, and you could potentially miss attackers more easily than if you selected medium or high. On the other hand, if you select high, you might see more events and also, potentially, more false positives. The default level is medium. For more information on these levels, see Pre-defined sensitivity levels for portscan detection, on page 1.

As you select the levels, you can see the related values within the protocol sections: **TCP**, **UDP**, **IP**, and **ICMP**. If you change any of the preset values, or disable a type of scan, the sensitivity mode automatically changes to **Custom**.

Within each protocol section, the options are:

- **Interval**—The time range, in seconds, within which the configured values for portscan or portsweep are exceeded. For example, if you select 90 seconds, and 60 as the number of TCP portscan ports, a scanner would need to try 60 ports on a host within 90 seconds for it to be considered a portscan. The system generates events only if the number of ports, protocols, or hosts (for a portsweep) are exceeded within the specified interval.

  You can specify a range between 30 to 600 seconds. The longer the period, the more likely a host might be identified as a scanner.

- **Portscan** (TCP/UDP)—Select whether to monitor for port scanning against single hosts, and specify the number of ports that must be scanned within the interval to count as a portscan attack. The allowed range is 1-256.
- **Portsweep** (TCP/UDP)—Select whether to monitor for port sweeping against multiple hosts, and specify the number of hosts that must be scanned for a given port within the interval to count as a portsweep attack. The allowed range is 1-256.
- **Protocol Scan** (IP)—Select whether to monitor for protocol scanning against single hosts, and specify the number of protocols that must be scanned within the interval to count as a protocol scan attack. The allowed range is 1-255.
- **Protocol Sweep** (IP)—Select whether to monitor for protocol sweeping against multiple hosts, and specify the number of hosts that must be scanned for a given protocol within the interval to count as a protocol sweep attack. The allowed range is 1-256.
- **Hostsweep** (ICMP)—Select whether to monitor for ICMP host sweeping against multiple hosts, and specify the number of hosts that must be scanned within the interval to count as a hostsweep attack. The allowed range is 1-256.

Step 5 If you selected prevention mode, click the **Prevention** tab and configure the options.

In prevention mode, hosts are automatically blocked from further scanning of networks on all protocols for the configured duration. Review the detection and prevention parameters carefully to ensure legitimate traffic is not blocked.

- **Exclude**—Select the network objects that define the hosts or networks, from within the range of the monitored networks, that should be excluded from automatic blocking. Even if these hosts violate your scanning detection parameters, the system will not block them.
- **Duration**—How long, in seconds, automatically blocked scanner hosts should be prevented from sending traffic of any kind through the device. After the duration period ends, the hosts are automatically cleared and can again send traffic through the device. The allowed range is 600 to 2592000 seconds. The default is 3600 seconds (1 hour).

  If you need to manually unblock a host, SSH to the firewall that is blocking the host and use the **clear threat-detection portscan attacker** command.

Step 6 Click **OK** to save the threat detection settings.

Step 7 Click **Save** to save the access control policy.

What to do next

Deploy configuration changes; see Deploy configuration changes.

Monitoring threat detection

The following topics explain how to monitor portscan activity.

View portscan alerts

Portscan activity is alerted through the existing portscan-specific intrusion events. Intrusion events with generator ID (GID) 122 and Snort ID from SIDs 1 through 27 are generated. For these events, the *(port_scan)* string is prepended in the event messages. The events include packet information along with packet data containing the statistics that triggered the alert.

To see portscan events, go to **Analysis** > **Intrusions** > **Events**.

Portscan issues these events regardless of your intrusion policy or NAP configuration. Events are issued only when scanners exceed the number of configured ports, protocols, or hosts for the various types of scan or sweep within the configured time interval for the associated protocol. A port scan from one host generates one event per set interval as soon as the threshold is met. If the same host initiates a new port scan during the same interval, no event is reported.

Table 2: Portscan events

Portscan type	Intrusion event
TCP Regular, Decoy, Distributed Scan	122:1 (port_scan) TCP portscan
TCP Portsweep	122:3 (port_scan) TCP portsweep
TCP Distributed Scan	122:4 (port_scan) TCP distributed portscan
IP Regular, Decoy, Distributed Protocol Scan n	122:9 (port_scan) IP protocol scan
IP Protocol Sweep	122:11 (port_scan) IP protocol sweep
IP Distributed Scan	122:12 (port_scan) IP distributed protocol scan
UDP Regular, Decoy, Distributed Scan	122:17 (port_scan) UDP portscan
UDP Portsweep	122:19 (port_scan) UDP portsweep
UDP Distributed Scan	122:20 (port_scan) UDP distributed portscan
ICMP Sweep	122:25 (port_scan) ICMP sweep
Portscan Block	122:100 (port_scan) host blocked due to portscan activity

Monitor portscan on the firewall

To monitor portscan, log in to the device Command-Line Interface (CLI) and use these commands.

- **show threat-detection portscan** [**attacker** | **target** | **shun**]

  Shows the IP addresses of scanners, those that have been shunned (blocked), and hosts that have been targeted by scans or sweeps.

- **show threat-detection portscan statistics** [**host** [*ipv4_address* | *ipv6_address*]] [**protocol** {**tcp** | **udp** | **IP** | **icmp**}]

Shows statistics related to the port scan system. You can specify host, protocol, or host and protocol to filter the output to the desired information.

- **clear threat-detection portscan** [**attacker** | **target** | **shun**] [*ipv4_address mask* | *ipv6_address/prefix*]

  Manually unblocks scanners (attackers) or identified targets. Enter the command without parameters to clear all attackers, targets, or shunned hosts.

- **clear threat-detection portscan statistics** [**host** [*ipv4_address* | *ipv6_address*]] [**protocol** {**tcp** | **udp** | **IP** | **icmp**}]

  Erases statistics related to portscan, so that you can more clearly see the current state of scanning through this device. Enter the command without parameters to clear all statistics. Alternatively, specify a host, protocol, or host and protocol, to limit the reset to the specified items.

Unblocking a host

If you configure threat detection in prevention mode and the system blocks a host that you know is not an attacker, you can manually unblock the host before the host is automatically unblocked when the duration period expires.

To manually unblock the host, log in to the device CLI where the host is blocked and enter the clear threat-detection portscan attacker command. For example:

```
> clear threat-detection portscan attacker 10.2.0.100 255.255.255.255
1 tracker object deleted and 1 shun entry removed
```

Consider adding the host IP address to the exclude list in the prevention configuration.

History for threat detection

This reference provides a chronological history of changes and enhancements made to the threat detection feature across different software releases.

Feature	Minimum Firewall Management Center	Minimum Firewall Threat Defense	Description
Improved portscan detection.	7.2	7.2 running Snort 3	With an improved portscan detector, you can easily configure the system to detect or prevent portscans. You can refine the networks you want to protect, set the sensitivity, and so on. For devices running Snort 2 and for devices running Version 7.1 and earlier, continue to use the network analysis policy for portscan detection. New/modified screens: We added **Threat Detection** to the access control policy's **Advanced** tab. New/Modified commands: **clear threat-detection portscan**, **show threat-detection portscan**.